

Musitel 70 - 72 - 74

“SMS en cas de non réponse”

Lorsque le CLIP du Musitel est caché, l'appelé ne peut connaître l'origine de l'appel qu'il a raté. Il reste, bien sur, la possibilité de dicter un message dans la boîte vocale du GSM appelé, pour autant qu'elle soit activée.

Une autre solution consiste à envoyer automatiquement un SMS invitant à rappeler le bureau. L'envoi de cet SMS est conditionné par le temps pendant lequel vous laissez sonner le GSM. Le message transmis peut comprendre maximum 160 caractères. Cette fonction est indépendante de l'envoi ou non du CLIP du Musitel. (Voir “GSM basic parameters” >>> “Calling ligne ident. Restr. CLIR”)

Fonctionnement :

Envoi automatique d'un SMS en cas de non réponse :

Vous appelez un GSM, il ne répond pas, vous devez laisser sonner plus de 30 secondes, puis raccrocher. Un SMS pré-configuré sera automatiquement envoyé à l'appelé.

Pas d'envoi d'un SMS en cas de non réponse :

Vous appelez un GSM, il ne répond pas, vous devez laisser sonner moins de 30 secondes, puis raccrocher.

Programmation

The screenshot shows the 'General routing parameters' configuration window. On the left is a tree view with 'General parameters' selected. The main area contains several sections: 'PBX mode' (unchecked), 'Operator 1' (Number: 111, Port: NT1), 'Operator 2' (Number: 666, Port: NT1), 'Dialing parameters' (Waiting for first digit: 10, Waiting for next digit: 4), 'DISA' (First digit waiting time: 10, Next digit waiting time: 4, Number of DDI digits: 3, Port: NT1), 'Call forwarding timeout' (0), 'DISA on TE port' (Password: empty), 'Waiting time for 1st number (s)' (20), 'Waiting time for next number (s)' (8), 'Unknown CLIP enabling' (checked), 'Enable only for CLIP tab numbers' (unchecked), 'Auto CLIP routing Validity (Hours)' (24), 'Erase after using' (unchecked), 'Store connected calls' (unchecked), and 'Local prefix when incoming international call' (0, ex. replace by incoming calls +32 with 0). The 'SMS at no answer' section is circled in red and contains: 'SMS at no answer' (checked), 'Delay' (30), and 'Text' (Rappelez le bureau svp).

General routing parameters

“SMS at no answer”

“Delay”

“Text”



Temps de sonneries nécessaire pour provoquer l'envoi de l'SMS.
Texte du message SMS.